

Wiring instructions for LED Stairwell Fixture with Emergency Battery Backup

Ordering Codes: SWFS4 | EB10

INSTRUCTIONS

1. Remove the purple sensor dimming wire (Dim+) from the driver's terminal block and connect it to the yellow emergency dimming wire (Dim+) using a wire nut.
2. Connect the purple emergency dimming wire (Dim+) to the driver's Dim+ terminal block.
3. Connect the gray emergency dimming wire (Dim-) and gray sensor dimming wire (Dim-) into the driver's Dim- terminal block.
4. Connect the brown and blue emergency output wires to the black and white driver input wires.
5. Connect the white, red and black emergency input wires in accordance with the following wiring diagram.

WIRING DIAGRAM

