

Dimmer Compatibility

LED Arch Light Panel (APT2S)



Dimmer Brand	Model Number	Load	APT2S Arch Panel
			36W
Lutron	NTSTV-DV	8A	1-19
	NFTV	5A	1-12
	DVTV	16A (Requires Power Pack PP-DV)	1-38
	DVSCTV		
	DVSTV	8A	1-19
	DVSCSTV		
	MS - Z101		
	MS - Z101 - V		
	RMJ-5T-DV-B	5A	1-12
	RMJS-8T-DV-B	8A	1-19
	FCJS-010	1A or 6mA of 0-10V	2
Leviton	DS710-10Z	1200VA@120V, 1500VA@277V	1-24
	IP710-DLX		
	IP710-DLZ		
	IP710-LFZ		
	AWRMG-7DW	1920W@120V, 4432W@277V	1-38
	AWSMT-7DW		
	AWSMG-7DW		
Eaton (Cooperindustries, Cooper Wiring Devices)	DF10P	1200W@120V, 1660W@277V	1-24
	SF10P		
Legrand (Pass & Seymour)	H4FBL3PTW	10A@120V, 5A@277V	
	WS4FBL3PTC		
	WS4FBL3PW		
Philips Lighting Controls	SR1200ZTUNV	1200VA@120V, 1500VA@277V	

(Minimum number of lamps per dimmer - maximum number of lamps per dimmer)

* LITETRONICS tests up to 3 lamps per dimmer;
maximum number of lamps calculated on the basis of capacity of dimmer.