

# Dimmer Compatibility

## LED Hazardous Location High Bay



DIMMER BRAND	MODEL #	LOAD	HAZARDOUS LOCATION HIGH BAY	
			150W (0-10V)	200W (0-10V)
Lutron	NTSTV-DV	8A	1-4	1-3
Lutron	NFTV	5A	1-3	1-2
Lutron	DVTV	16A (Requires Power Pack PP-DV)	1-9	1-6
Lutron	DVSCTV	16A (Requires Power Pack PP-DV)	1-9	1-6
Lutron	DVSTV	8A	1-4	1-3
Lutron	DVSCSTV	8A	1-4	1-3
Lutron	MS - Z101	8A	1-4	1-3
Lutron	MS - Z101 - V	8A	1-4	1-3
Lutron	RMJ-5T-DV-B	5A	1-3	1-2
Lutron	RMJS-8T-DV-B	8A	1-4	1-3
Lutron	FCJS-010	1A or 6mA of 0-10V		
Leviton	DS710-10Z	1200VA@120V, 1500VA@277V	1-5	1-4
Leviton	IP710-DLX	1200VA@120V, 1500VA@277V	1-5	1-4
Leviton	IP710-DLZ	1200VA@120V, 1500VA@277V	1-5	1-4
Leviton	IP710-LFZ	1200VA@120V, 1500VA@277V	1-5	1-4
Leviton	AWRMG-7DW	1920W@120V, 4432W@277V	1-9	1-6
Leviton	AWSMT-7DW	1920W@120V, 4432W@277V	1-9	1-6
Leviton	AWSMG-7DW	1920W@120V, 4432W@277V	1-9	1-6
Eaton ( Cooperindustries, Cooper Wiring Devices )	DF10P	1200W@120V, 1660W@277V	1-5	1-4
Eaton ( Cooperindustries, Cooper Wiring Devices )	SF10P	1200W@120V, 1660W@277V	1-5	1-4
Legrand ( Pass & Seymour )	H4FBL3PTW	10A@120V, 5A@277V	1-5	1-4
Legrand ( Pass & Seymour )	WS4FBL3PTC	10A@120V, 5A@277V	1-5	1-4
Legrand ( Pass & Seymour )	WS4FBL3PW	10A@120V, 5A@277V	1-5	1-4
Philips Lighting Controls	SR1200ZTUNV	1200VA@120V, 1500VA@277V	1-5	1-4